# CINCH

# CeLAN Printer Module

DS-Ce-P Rev A

## <u>General</u>

The CeLAN Printer Module allows you to connect a parallel printer to any Protector panel. The module allows you to print (or log) events as they occur. The module also includes a zone input that can be used as a tamper or any other system input.

Power for the CeLAN Printer Module is provided by, the Protector 12 VDC CeLAN power terminals, CeLAN Remote Power Module, or a separate 12 VDC-power supply capable of delivering up to 63 mA.

CeLAN AES encrypted digital data bus technology provides secure, fast and reliable data transfer between the Protector Panel and CeLAN modules.





CO-T-Printer

Printer Emulation Module, provides an output to a PC via USB cable.

Printer Module Mounting:

E-PA - Knockout available for printer connection

Encrypted Receiver - Mounting standoffs available in back of receiver enclosure

### Features

- CeLAN AES encrypted technology for security, easy setup and enhanced performance
- Single 25-pin "Centronics" Parallel Connector
- One (1) fully supervised input zone
- Five (5) state zones:
  - Open Circuit
  - Supervised Circuit (3.0k EOL)
  - Short Circuit
  - Ground Fault High
  - Ground Fault Low

- On-board LED power and CeLAN bus status indicators
- Includes Accessory Hardware kit
- Mounts inside Protector, Protector Accessory, or CeLAN AES Encrypted Receiver
- CINCH Stick' Field Upgradeable firmware



Printer Module mounted inside an Encrypted Receiver

# **CeLAN** Printer Module

# Specifications

#### **Power Requirements:**

- Input: 12 VDC (8 VDC min, 14 VDC max)
- Output: N/A •
- Current Draw: 63 mA standby, 72mA max •
- Dimensions: 8.26" x 5.24" (LxW)

#### **Environmental:**

- Operation Temp: 32 to 120 F (0 to 49 C) •
- Humidity: 90% relative humidity
- Storage Temp: -30 to 140 F (-• 34 to 60 C)
- **Inputs:** 1 supervised input •
- **CELAN Devices per System:** 100
- Supervision: 3K Ohm Resistor
- **Encryption:** 128 bit AES
- Accessories:
  - Plastic Enclosure: E-CP •
  - Small metal enclosure: E-PA-S •
  - Medium metal enclosure: E-PA
- **Compatibility:** Protector
- Listings:
  - UL: 1076
  - FCC: Part 15
  - FIPS 197 Cert #1125

### Ordering

**Control Panel** PCU-IDS Protector Panel

**Touch Screen** Ce-TS Touch Screen

#### **Expansion Modules**

Ce-2ZI 2 Zone Input Ce-8ZI 8 Zone Input Ce-4RO 4 Relay Output Ce-24ZI 24 Zone Input

#### **Communication Modules** Ce-FC-N Fiber Conversion

Ce-TCP/IP Network Module Ce-FC-ER Fiber Conversion

#### **CeLAN Modules** Ce-DS938Z Motion Ce-DS308 Motion Ce-DSISC Motion Ce-M3ZS HSS L2 Contact Ce-M1ZRS Recessed Contact Ce-1076DRS Recessed Contact Ce-1076HRS Recessed Contact Ce-U1Z Universal 1 Zone

## Ce-U2Z Universal 2 Zone Receivers

Ce-AESR-IDS AES Receiver

Ce-WF2ZI Wellsfargo Contact

### **CeLAN Accessories**

ධංධ 🛛 ධංධපටපටපටපටපට වේ ය. ය.ටපටපට מימימים"ם ממימים ממימים מימים מימ

õõ

 $\Box$ 

00000

CO-CSU Cinch Stick CO-PS2KI Keyboard Module CO-T-P Panel Tester CO-T-8Z 8 Zone Tester CO-T-4R 4 Relay Tester CO-T-Printer Printer Tester CO-PRSI Siren Supervision Ce-EX Expansion Module

#### Power

ACC-24T-100 Transformer ACC-B12-18 18Ahr Battery ACC-B12-7 7Ahr Battery ACC-6P Power Cord E-CB Termination Box


#### Accessories

Single hardwire zone

L-M-KD Panel Lock L-M-KA Panel Lock ACC-CFC-S Fiber Cable L-S Standard Panel Lock ACC-CFC-MM Fiber Cable S-ET Panel Tamper

#### Enclosures

E-P Panel Enclosure E-P-Kit E-CP Plastic Enclosure E-PA Accessory Enclosure E-PA-Kit E-PA-S Small Accessory Enclosure E-PA-S-Kit



Cinch Systems 10275 43rd St NE, Ste 300 St Michael, MN 55379 1-763-497-1059

# SECURITY AES ENCRYPTED





DPU 414 Parallel Printer (not available from Cinch)

